


IES2312 Series Unmanaged Industrial PoE/non-PoE Ethernet Switch Quick Installation Guide



3onedata Co., Ltd.

Address: 3/B, Zone 1, Baiwangxin High Technology Industrial Park, Xili, Nanshan District, Shenzhen

Website: www.3onedata.com
Tel: +86 0755-26702688
Fax: +86 0755-26703485

【Package Checklist】

Please check whether the package and accessories are intact while using the switch for the first time. The following list is the standard configuration, please follow up the real product.

1. Industrial Ethernet switch
2. Certification
3. Quick installation guide
4. Warranty card

If any of these items are damaged or lost, please contact our company or dealers, we will solve it ASAP.


【Product Overview】

The series of product are unmanaged DIN-Rail industrial PoE/non-PoE Ethernet switches. Model as follows:

- Model I IES2312-8GP4GF-2P24-120W(8 Gigabit PoE ports + 4 Gigabit fiber ports, 24VDC PoE, PoE power of 120W)
- Model II IES2312-8GP4GS-2P24-120W(8 Gigabit PoE ports + 4 Gigabit SFP slots, 24VDC PoE, PoE power of 120W)
- Model III IES2312-8GP4GF-2P48-120W(8 Gigabit PoE ports + 4 Gigabit fiber ports, 48VDC PoE, PoE power of 120W)
- Model IV IES2312-8GP4GS-2P48-120W(8 Gigabit PoE ports + 4 Gigabit SFP slots, 48VDC PoE, PoE power of 120W)
- Model V IES2312-8GP4GF-2P48-240W(8 Gigabit PoE ports + 4 Gigabit fiber ports, 48VDC PoE, PoE power of 240W)
- Model VI IES2312-8GP4GS-2P48-240W(8 Gigabit PoE ports + 4 Gigabit SFP slots, 48VDC PoE, PoE power of 240W)
- Model VII IES2312-8GT4GF-2P48(8 Gigabit copper ports + 4 Gigabit fiber ports, 12~48VDC)
- Model VIII IES2312-8GT4GS-2P48(8 Gigabit copper ports + 4 Gigabit SFP slots, 12~48VDC)
- Model IX IES2312-8GT4GF-P220(8 Gigabit copper ports + 4 Gigabit fiber ports, 100~240VAC)
- Model X IES2312-8GT4GS-P220(8 Gigabit copper ports + 4 Gigabit SFP slots, 100~240VAC)

【Panel Design】


➤ **Top view, Bottom view and Rear view**



3. DIP switch (reserved)
4. Console port (reserved)
5. Grounding screw
6. Wall mounting screw hole
7. DIN-Rail mounting kit
8. Power supply indicator P1/P2/PWR
9. Relay alarm indicator ALM
10. Device running indicator RUN
11. PoE indicator PoE+
12. Interface connection indicator Link
13. Gigabit PoE port
14. Gigabit fiber port
15. Gigabit copper port
16. Gigabit SFP slot

【Mounting Dimension】

Unit: mm



Notice:

The hanging panel accessories on the right side of the picture above need additional purchase.



Attention before mounting:


- Don't place or install the device in area near water or moist, keep the relative humidity of the device surrounding between 5%~95% without condensation.
- Before power on, first confirm the supported power supply specification to avoid over-voltage damaging the

device.

- The device surface temperature is high after running; please don't directly contact to avoid scalding.

【DIN-Rail Mounting】

For convenient usage in industrial environments, the product adopts 35mm DIN-Rail mounting, mounting steps as below:



- Step 1 Check if the DIN-Rail mounting kit is installed firmly.
- Step 2 Insert the bottom of DIN-Rail mounting kit (one side with spring support) into DIN-Rail, and then insert the top into DIN-Rail.

Tips:

Insert a little to the bottom, lift upward and then insert to the top.

- Step 3 Check and confirm the product is firmly installed on DIN-Rail, then mounting ends.

【Disassembling DIN-Rail】

- Step 1 Device power off.
- Step 2 After lift the device upward slightly, first shift out the top of DIN-Rail mounting kit, then shift out the bottom of DIN-Rail, disassembling ends.




Attention before power on:

- Power ON operation: first connect power line to the connection terminal of device power supply, then power on.
- Power OFF operation: first unpin the power plug, then remove the power line, please note the operation order above.

【Power Supply Connection】

- DC power supply



The series provide 6 pins 5.08mm pitch terminal blocks and two independent DC power supplies of PWR1 and PWR2. This series provide 8 types of product and adopt 4 different power supply ranges.

Please be aware of the corresponding power supply type of the device lest damaging the device.

24VDC PoE device

The power supply of 24VDC PoE device model I and model II has built-in 12A over-current protection, and support anti-reverse connection and redundant backup. Input power is 24VDC.

48VDC PoE device

The power supply of 48VDC PoE device model III, model IV, model V, and model VI has built-in 5A over-current protection, and support anti-reverse connection and redundant backup. Input power is 48VDC.

12~48VDC non-PoE device

The power supply of 12~48VDC non-PoE device model VII and model VIII has built-in 3A over-current protection, and support non-polarity and redundant backup. Input power range is 12~48VDC.

➤ AC power supply



The series provide 6 pins 5.08mm pitch terminal blocks and AC power supply system.

220VAC non-PoE device

The power supply of 220VAC non-PoE device model IX and model X has built-in 5A over-current protection. Input power range is 100~240VAC.

【Checking LED Indicator】

This device provides LED indicators to monitor device's operating state, which has simplified the troubleshooting process comprehensively. The status of each LED is described in the table below:

LED	Status	Description
-----	--------	-------------

RUN	ON	The device is powered on or the device is abnormal.
	OFF	The device is powered off or the device is abnormal.
	Blinking	Blink 1 time/s, the device runs normally
P1/P2/PWR	ON	Power supply P1/P2/PWR is connected and running normally
	OFF	Power supply P1/P2/PWR is disconnected and running abnormally
Link G1-G12	ON	Ethernet port has established valid network connection
	Blinking	Ethernet port is in active status
	OFF	Ethernet port has not established valid network connection
POE G1-G8	ON	PD device is powered over PoE port normally
	OFF	PD device is not powered over PoE or not connected to PoE

【Specification】

Panel	
Gigabit PoE port	10/100/1000Base-T(X), RJ45, automatic flow rate control, full/half duplex mode, MDI/MDI-X autotuning; PoE power supply pins: V+, V+, V-, V. Output power is 30W
Gigabit copper port	10/100/1000Base-T(X), RJ45, automatic flow rate control, full/half duplex mode, MDI/MDI-X autotuning
Gigabit fiber port	1000Base-FX, optional SC/ST/FC interface
Gigabit SFP slot	1000Base-SFP, LC
Console port	Reserved

Alarm port	Reserved
Indicator	Power indicator, run indicator, interface connection indicator and PoE indicator
Switch property	
Backplane bandwidth	24G
Buffer size	4Mbit
MAC address table	8K
Power supply	
Model I, Model II	24VDC PoE, anti-reverse connection, redundant backup, built-in 12A over-current protection
Model III, Model IV, Model V, Model VI	48VDC PoE, anti-reverse connection, redundant backup, built-in 5A over-current protection
Model VII, Model VIII	12~48VDC, non-polarity, redundant backup, built-in 3A over-current protection
Model IX, Model X	100~240VAC, built-in 5A over-current protection
Terminal block	6-pin 5.08mm pitch terminal blocks, power supply occupies 4 pins
Power consumption	
Model I	No-load: 9.1W@24VDC Full-load: 141.5W@24VDC
Model II	No-load: 6.0W@24VDC Full-load: 100.8W@24VDC
Model III	No-load: 8.8W@48VDC Full-load: 130.0W@48VDC
Model IV	No-load: 5.2W@48VDC Full-load: 132.9W@48VDC
Model V	No-load: 8.8W@48VDC Full-load: 199.6W@48VDC
Model VI	No-load: 5.2W@48VDC Full-load: 200.2W@48VDC

Model VII	No-load: 7.5W@24VDC Full-load: 10.5W@24VDC
Model VIII	No-load: 4.2W@24VDC Full-load: 10.2W@24VDC
Model IX	No-load: 7.7W@220VAC Full-load: 11.1W@220VAC
Model X	No-load: 4.6W@220VAC Full-load: 10.4W@220VAC
Operating environment	
Operating temperature	-40~75℃
Storage temperature	-40~85℃
Operating humidity	5%~95% (no condensation)
Protection grade	IP40 (metal shell)